

OPTICAL COMPONENT DRIVING DEVICE IN LASER APPARATUS

BACKGROUND OF THE INVENTION

Field of the Invention

The present invention relates to a driving device which changes the orientation angle of optical components in laser apparatus.

Description of the Related Art

When an excimer laser or molecular fluorine F2 laser is used as a stepper light source, the oscillated laser light must be subject to line-narrowing. Also, in order to prevent the central wavelength of the spectrum of the oscillated laser light with narrowed linewidth from being deviated from the target value during exposure, stability control must be performed precisely.

FIG. 4(a) shows a construction surrounding a line-narrowing unit 9 mounted on a conventional laser apparatus. Alternate long and short dash lines in FIG. 4(a) show optical axes of laser light L. FIG. 4(b) is a cross-sectional view taken along line IV-IV in FIG. 4(a).

The linewidth narrowing effect is achieved by reflecting the laser light at a certain fixed angle of incidence (angle of reflection) ϕ relative to a reflector-type wavelength selecting element, or grating 2, installed inside the line-narrowing unit 9. The reflector-type wavelength selecting element 2 is an optical component that selects a wavelength by reflecting the laser light L. Reflector-type wavelength selecting element 2 selects a wavelength that corresponds to the angle of incidence (angle of reflection) ϕ . The angle of incidence ϕ is determined by the orientation angle θ of the reflection mirror 3

which totally reflects the incident laser light L and directs it onto the reflector-type wavelength selecting element 2. The orientation angle θ of reflection mirror 3 is changed by linear movement of a feed screw 16a (male screw) of the feed screw unit 16 in the directions of arrows B. With rotational
5 movement of a control motor 8 as shown by arrow C, the feed screw 16a moves linearly.

During exposure the control motor 8 is drive controlled so as to make the deviation of the central wavelength of the oscillated laser spectrum to be extremely small. Specifically, clockwise or anticlockwise rotation of the
10 drive shaft 8a of the control motor 8, as shown by arrows C, makes the feed screw 16a to rotate in the same direction C as the drive shaft 8a. Rotation of the feed screw 16a results in its reciprocal movement in the direction of arrow B, thus determining the feed position of the feed screw 16a. This, in turn, determines the orientation angle θ of the reflection mirror 3 and the
15 angle of incidence ϕ of the light relative to the reflector-type wavelength selecting element 2, and the central wavelength of the laser light L spectrum is thereby fixed at the target wavelength.

Here, a so-called high-precision screw is used for the feed screw unit 16. The high-precision feed screw is machined so as to make the clearances
20 between the feed screw 16a (male screw) and the nut 16b (female screw) to be extremely small. Specifically, each pair of feed screw 16a and nut 16b is managed by spot goods control. To reduce the contact friction between the feed screw 16a and the nut 16b, a lubricant (grease) is applied in abundant quantity onto a part D where the feed screw 16a and the nut 16b are contact
25 with each other.

However, even if the thread clearances in the feed screw unit 16 can be made very small by spot goods control, it is structurally impossible to make

them extremely small, and very small thread clearances inevitably exist. In other words, the backlash in the feed screw unit 16 cannot be completely eliminated. Therefore, when the control motor 8 rotates back and forth in the direction of arrows B, and the feed screw 16a moves reciprocally in the directions of arrows B, precision of positioning the reflection mirror 3 is impaired. And if the precision of positioning the reflection mirror 3 is impaired, precision of controlling wavelength of laser light L to be a target value is impaired, resulting in impaired wavelength stability. In other words, there is a problem of decreased precision in controlling wavelength and decreased wavelength stability.

Another drawback of the conventional feed screw unit 16 is that, due to very small thread clearances, significant friction resistance exists during operation of the feed screw unit 16. This leads to increased rotation torque of control motor 8 that is necessary for driving the feed screw unit 16. This results in poor linear movement response of the feed screw 16a to the drive command to the control motor 8, and a considerable time is required to change the wavelength of the laser light L to the target wavelength. Therefore, there is a problem of decreased speed of wavelength control.

In order to decrease the friction resistance during operation of the feed screw unit, it is necessary to apply an abundant quantity of a lubricant on contact section D. However, contact section D communicates with the interior of the line-narrowing unit 9. The excimer laser light L of deep ultraviolet wavelength zone scatters within the line-narrowing unit 9. This deep ultraviolet light irradiates the lubricant and may promote the chemical decomposition reaction of the lubricant. If the decomposition reaction of the lubricant proceeds, the impurities thereby produced will pollute optical components located inside the line-narrowing unit 9, and the performance of the laser apparatus may be impaired. Therefore, there is a problem of poor

performance of the laser apparatus resulting from pollution of optical components.

OBJECTS AND SUMMARY OF THE INVENTION

5 With the foregoing in view, it is an object of the present invention to improve precision of wavelength control and wavelength stability, to increase speed of wavelength control and to prevent optical components from being polluted.

10 To achieve this object, the present invention provides an optical component driving device provided in a laser apparatus, comprising an optical component (3) that changes wavelength of the laser light (L) in accordance with an orientation angle (θ) thereof, and a feed screw mechanism (6) that converts rotational movement of a rotary actuator (8) into linear movement of a feed screw (6a), the orientation angle (θ) of the optical
15 component (3) being changed in accordance with the linear movement of the feed screw (6a) of the feed screw mechanism (6), characterized in that the feed screw (6a) of the feed screw mechanism (6) is a ball screw (6a).

 The present invention will be described with reference to FIGS. 1(a) and 1(b):

20 The ball screw unit 6 is a feed screw mechanism that is used by previously applying a load (pre-load) between a ball screw 6a and a nut 6b and in which the ball screw 6a moves linearly by the sliding of the ball. This construction permits to make the mechanical screw clearances to be very small, thus making it possible to eliminate the backlash of the ball screw unit
25 6, or to make it non-backlash. Since there is no screw clearance, it is possible to improve the precision of positioning the reflection mirror 3 when the control motor 8 rotates clockwise and anticlockwise as shown by arrows C,

and the screw 16a moves reciprocally as shown by the arrows B. Better precision of positioning of the reflection mirror 3 results in improvement in precision of controlling the wavelength of the laser light L to the target wavelength, and improvement in wavelength stability

5 Since the ball screw 6a is caused to move linearly by the sliding of the balls, friction resistance during operation of the ball screw unit 6 is low. Therefore, smaller torque of the control motor 8 is required to drive the ball screw unit 6. As a result, linear movement response of the ball screw 6a to the drive command to the control motor 8 can be increased, while the time
10 required for adjustment of the wavelength of the laser light L to the target value can be reduced.

Furthermore, due to better wavelength control precision and reduced time of adjustment of light wavelength to the target value, the speed of wavelength control can be increased.

15 Due to low friction resistance of the ball screw unit 6, the amount of lubricant applied to contact portion D can be minimized. As a result, in spite of deep ultraviolet light irradiating the lubricant, the amount of resulting impurities is negligible. This makes it possible to minimize pollution of optical components located inside the line-narrowing unit 9 and to prevent
20 deterioration of the laser apparatus performance.

BRIEF DESCRIPTION OF THE DRAWINGS

FIG. 1 (a) is a diagram showing an embodiment of an optical component driving device, and FIG. 1 (b) is a cross-sectional view taken
25 along line I-I in FIG. 1 (a);

FIG. 2 is a graph showing the advantages of the device according to the embodiment of the present invention, wherein wavelength zones of the

laser light are plotted on the horizontal axis, and error ranges for the wavelength control of laser light are plotted on the vertical axis;

FIG. 3 is a graph showing advantages of the device according to the embodiment, wherein amounts of adjustment of a laser light wavelength are plotted on the horizontal axis and time periods required for these adjustments are plotted on the vertical axis; and

FIG. 4 (a) is a diagram showing a conventional optical component driving device, and FIG. 4 (b) is a cross-sectional view taken along line IV-IV in FIG. 4 (a).

10

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

An embodiment of the optical component driving device provided in the laser apparatus of the present invention will be described below with reference to figures. It is assumed that in this embodiment the laser apparatus is used as a stepper light source.

FIG. 1 (a) shows the embodiment of the optical component driving device. FIG. 1 (a) shows the construction surrounding the line-narrowing unit 9 mounted on the laser apparatus. Alternate long and short dash lines in FIG. 1 (a) show optical axes of the laser light L. FIG. 1 (b) is a cross-sectional view taken along line I-I in FIG. 1 (a).

20

Firstly, functions of the line-narrowing unit 9 used in the laser apparatus will be described.

The laser light L oscillated by discharge excitation in a laser chamber (not shown) is amplified by causing the laser light to travel reciprocally within a resonator that is constituted from a front mirror and the line-narrowing unit 9, and then emitted from the front mirror as a laser light with a prescribed power. In this embodiment, the laser light L travels reciprocally

between the front mirror and the reflector-type wavelength selecting element 2.

Optical components consisting of, for example, two prisms 1a and 1b a reflection mirror (total reflection mirror) and a reflector-type wavelength selecting element (grating) 2 are provided inside the line-narrowing unit 9. Incidentally, any number of the prisms can be provided as desired. The prisms 1a, 1b and the reflector-type wavelength selecting element 2 are fixed on the bottom plate of the line-narrowing unit 9. The reflection mirror 3 is held by a reflection mirror holding member (mirror holder) 4. The reflection mirror holding member 4 is supported rotatably by a supporting member 5. As the reflection mirror holding member 4 turns around the point at which it is supported by the supporting member 5, the orientation angle θ of the reflection mirror 3 changes according to the turning thereof. A driving mechanism that turns the reflection mirror holding member 4 and changes the orientation angle θ of the reflection mirror 3 will be described later.

The laser light L oscillated in the laser chamber enters the line-narrowing unit 9 and passes through the prisms 1a, 1b that act as beam expanders, whereby the beam width of the laser light L is expanded. The expanded laser light L impinges the reflection mirror 3 and, after being fully reflected, impinges on the reflector-type wavelength selecting element 2. The laser light L impinging upon the reflector-type wavelength selecting element 2 is diffracted, and only a part of the laser light L with a prescribed wavelength is sent back in the same direction as the incident light. The beam width of the laser light L that has been sent back by the reflector-type wavelength selecting element 2, is reduced by the prisms 1b, 1a, and then enters the laser chamber. After the laser light L has been passed through the laser chamber and amplified, a part thereof is outputted by way of the front

mirror as an output light, while the rest part is returned to the laser chamber and amplified.

When the laser apparatus is used as a stepper source, linewidth of the oscillated laser light must be narrowed. A stable and precise adjustment must be ensured to prevent the central wavelength in the spectrum of this oscillated laser light with narrowed linewidth from being deviated from the target value during exposure.

The linewidth is narrowed using the reflector-type wavelength selecting element 2. As stated above, the reflector-type wavelength selecting element 2 selects a wavelength by reflecting the incident laser light L. The reflector-type wavelength selecting element 2 selects a wavelength corresponding to the angle of incidence (angle of reflection) ϕ . The angle of incidence ϕ depends on the orientation angle θ of the reflection mirror 3 that directs the laser light L to the reflector-type wavelength selecting element 2.

Now the construction of the driving mechanism that changes the orientation angle θ of the reflection mirror 3 will be described.

The orientation angle θ of the reflection mirror holding member 4 is changed by the driving of the ball screw unit 6 which is a feed screw mechanism. The ball screw unit 6 consists of a ball screw 6a and a nut 6b. The ball screw unit 6 is a feed screw mechanism in which the ball screw 6a moves linearly relative to the nut 6b by the sliding of the ball. One end of the ball screw 6a abuts on the reflection mirror holding member 4. A flat spring 10 exerts a spring force on the reflection mirror holding member 4 in the direction in which the ball screw 6a abuts on the reflection mirror holding member 4.

The other end of the ball screw 6a is connected through a coupling 7 to the drive shaft 8a of the control motor 8. The nut 6b is in thread engagement the ball screw 6a and is fixed on the wall of the line-narrowing unit 9.

The control motor 8 is a stepping motor, a servo motor or the like, supported on a guide mechanism 11, such as LM guide, so as to be able to freely reciprocate in the direction of arrows B. The guide mechanism 11 is fixed to the outside of the line-narrowing unit 9.

Next, the operation of the optical component driving device will be described.

During exposure, the control motor 8 is controlled so as to make deviations of the central wavelength in the spectrum of the oscillated laser light to be extremely small. The control can be a feedback control or an open-loop control. When the feedback control is used, wavelength of the oscillated laser light is detected and inputted through the feedback loop to a controller (not shown).

The controller outputs a drive control signal to the control motor 8. In response to this drive control signal, the drive shaft 8a rotates clockwise or counter-clockwise as indicated by arrows C.

When the drive shaft 8a of the control motor 8 rotates in the direction of arrow C, the ball screw 6a rotates in the same direction C. As a result, the ball screw 6a moves linearly in the direction of arrows B relative to the nut 6b, i.e. relative to the line-narrowing unit 9. The ball screw 6a moves linearly in the directions of arrows B together with the control motor 8 that is connected to the ball screw 6a through the coupling 7. The control motor 8 moves along the guide of the guide mechanism 11 in the directions of arrows B.

When the ball screw 6a moves linearly relative to the line-narrowing unit 9 as described above, the reflection mirror holder 4 abutting on the ball

screw 6a is pivoted on the supporting member 5. As a result, the orientation angle θ of the reflection mirror 3 is changed. Thus, the reflection mirror 3 is positioned at a position corresponding to the linear movement position of the ball screw 6a.

When the orientation angle θ of the reflection mirror 3 is determined, then the angle of incidence ϕ in respect to the reflector-type wavelength selecting element 2 is determined and the central wavelength in the spectrum of the laser light L is fixed corresponding thereto.

Next, the advantages of the present invention will be described with reference to FIGS. 2 and 3.

In this embodiment, a ball screw unit 6 is used as a feed screw mechanism.

The ball screw unit 6 is a feed screw mechanism in which a load (pre-load) is previously applied between the ball screw 6a and nut 6b, and the ball screw 6a is moved linearly by the sliding of the balls. This makes it structurally possible to make mechanical thread clearance to be extremely small. Thereby, the back-lash of the ball screw unit 6 can be nullified, in other words, non back-lash ball screw unit can be realized. Since there is no screw clearance, the precision of positioning of the reflection mirror 3 can be improved, when the control motor 8 rotates clockwise and anticlockwise as shown by arrows B and the feed screw 16a moves linearly in the directions of arrows B. Higher precision of positioning of the reflection mirror 3 results in higher precision in controlling the laser light L to the target wavelength and higher wavelength stability.

FIG. 2 is a graph showing in comparison the difference in effects between the device of this embodiment shown in FIG. 1(a) and the conventional device shown in FIG. 4(a). On the horizontal axis, wavelength

00640700-122700

zones (in pm) of the laser light L are plotted that correspond to the orientation angles θ of the reflection mirror 3, and on the vertical axis, precision of positioning of the reflection mirror 3, i.e. error ranges (in pm) with respect to the target wavelength of the laser light L is plotted. Specifically, an error
5 range is shown for each wavelength zone, when the orientation angle θ of the reflection mirror 3 is changed by 12 pm. Characteristics of the device of this embodiment using the ball screw 6 is shown by 6C and characteristics of the conventional device using the precision screw 16 is shown by 16C.

As is obvious from a comparison of characteristics 6C and 16C, in all
10 wavelength zones the error ranges of the device of this embodiment are smaller than these of the conventional device, and wavelength control precision and wavelength stability are also higher in the device of this embodiment compared to the conventional device.

Furthermore, in the device of this embodiment, because the ball screw
15 6a is moved linearly by the sliding of the balls, the friction resistance during operation of the ball screw unit 6 is low. As a result, the torque of the control motor 8 required for driving the ball screw unit 6 can be small. Therefore, the responsibility of the linear movement of the ball screw 6a to the driving command to the control motor 8 is improved, and time required for
20 adjustment of the wavelength of the laser light L to the target wavelength can be reduced.

Moreover, due to reduced time required for adjustment of the wavelength of the laser light L to the target wavelength, the speed of the wavelength control can be increased.

25 FIG. 3 is a graph showing in comparison the difference in effects between the device of this embodiment shown in FIG. 1(a) and the conventional device shown in FIG. 4(a). On the horizontal axis, amounts of

wavelength adjustment (in μm) of the laser light L are plotted that correspond to the amounts of change of the orientation angle θ of the reflection mirror 3, and on the vertical axis, time periods required for adjusting the wavelength of the laser light L to the target wavelength (in sec) are plotted. Characteristics of the device of this embodiment using the ball screw 6 are shown by 6D and characteristics of the conventional device using the precision screw 16 are shown by 16D.

As is obvious from comparison of characteristics 6D and 16D, the required time of the device of this embodiment is shorter than that of the conventional device, while wavelength adjustment speed is higher than that of the conventional device.

Furthermore, in the device of this embodiment, due to lower friction resistance during operation of the ball screw unit 6, the amount of lubricant applied to contact portion D can be minimized and as little as possible. As a result, in spite of deep ultraviolet light irradiating the lubricant, amount of resulting impurities is very little, and pollution of optical components located inside the line-narrowing unit 9 can be minimized, whereby deterioration in performance of the laser apparatus can be prevented.

In the laser apparatus according to the present embodiment as described above, it is possible to improve wavelength control precision and wavelength stability and to increase wavelength control speed, as well as to prevent pollution of optical components.

Moreover, according to the present embodiment, the angle of incidence ϕ to the reflector-type wavelength selecting element 2 is changed by changing the orientation angle θ of the reflection mirror 3 that is used as the optical component, and thereby the wavelength of the oscillated laser light L is changed. However, the wavelength of the oscillated laser light L may be

1899	1900	1901	1902	1903	1904	1905	1906	1907	1908	1909	1910	1911	1912	1913	1914	1915	1916	1917	1918	1919	1920	1921	1922	1923	1924	1925	1926	1927	1928	1929	1930	1931	1932	1933	1934	1935	1936	1937	1938	1939	1940	1941	1942	1943	1944	1945	1946	1947	1948	1949	1950	1951	1952	1953	1954	1955	1956	1957	1958	1959	1960	1961	1962	1963	1964	1965	1966	1967	1968	1969	1970	1971	1972	1973	1974	1975	1976	1977	1978	1979	1980	1981	1982	1983	1984	1985	1986	1987	1988	1989	1990	1991	1992	1993	1994	1995	1996	1997	1998	1999	2000	2001	2002	2003	2004	2005	2006	2007	2008	2009	2010	2011	2012	2013	2014	2015	2016	2017	2018	2019	2020	2021	2022	2023	2024	2025	2026	2027	2028	2029	2030	2031	2032	2033	2034	2035	2036	2037	2038	2039	2040	2041	2042	2043	2044	2045	2046	2047	2048	2049	2050	2051	2052	2053	2054	2055	2056	2057	2058	2059	2060	2061	2062	2063	2064	2065	2066	2067	2068	2069	2070	2071	2072	2073	2074	2075	2076	2077	2078	2079	2080	2081	2082	2083	2084	2085	2086	2087	2088	2089	2090	2091	2092	2093	2094	2095	2096	2097	2098	2099	2100	2101	2102	2103	2104	2105	2106	2107	2108	2109	2110	2111	2112	2113	2114	2115	2116	2117	2118	2119	2120	2121	2122	2123	2124	2125	2126	2127	2128	2129	2130	2131	2132	2133	2134	2135	2136	2137	2138	2139	2140	2141	2142	2143	2144	2145	2146	2147	2148	2149	2150	2151	2152	2153	2154	2155	2156	2157	2158	2159	2160	2161	2162	2163	2164	2165	2166	2167	2168	2169	2170	2171	2172	2173	2174	2175	2176	2177	2178	2179	2180	2181	2182	2183	2184	2185	2186	2187	2188	2189	2190	2191	2192	2193	2194	2195	2196	2197	2198	2199	2200	2201	2202	2203	2204	2205	2206	2207	2208	2209	2210	2211	2212	2213	2214	2215	2216	2217	2218	2219	2220	2221	2222	2223	2224	2225	2226	2227	2228	2229	2230	2231	2232	2233	2234	2235	2236	2237	2238	2239	2240	2241	2242	2243	2244	2245	2246	2247	2248	2249	2250	2251	2252	2253	2254	2255	2256	2257	2258	2259	2260	2261	2262	2263	2264	2265	2266	2267	2268	2269	2270	2271	2272	2273	2274	2275	2276	2277	2278	2279	2280	2281	2282	2283	2284	2285	2286	2287	2288	2289	2290	2291	2292	2293	2294	2295	2296	2297	2298	2299	2300	2301	2302	2303	2304	2305	2306	2307</
------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	------	--------

13